



Theoretical Study on Planar Transmission Line Structure

Md. Abuzar Dilshad¹, Prof. (Dr.) Mahesh Dutta Singh²

¹Research Scholar, Department of Physics,

Veer Kunwar Singh University, Arrah, Bihar, India

²Pranav Chatterjee College, Mitralok Colony, Buxer, Bihar, India

Abstract:

Planar transmission lines are widely used for signal transmission in microwave, millimeter-wave, and high-frequency electronic systems. This paper presents a theoretical investigation of several planar transmission-line configurations, including image line, microstrip, fin line, inverted microstrip, slot line, trapped inverted microstrip, coplanar waveguide, coplanar strip/differential line, and strip line. Their fundamental operating characteristics are examined in terms of electromagnetic field distribution, propagation modes, operating-frequency range, transmission losses, characteristic impedance, fabrication requirements, and structural limitations. The study considers different propagation behaviors, including TEM, quasi-TEM, TE, and TM modes, and discusses their influence on transmission performance. The analysis shows that the electrical characteristics of planar transmission lines are closely related to their geometrical arrangement, dielectric environment, operating frequency, and conductive boundaries. Different structures provide specific advantages for particular applications, ranging from conventional microwave circuits to millimeter-wave systems. This theoretical study provides a comparative understanding of planar transmission-line configurations and their characteristics, limitations, and suitability for high-frequency circuit applications.

Keywords: *Planar transmission line; microstrip line; fin line; coplanar waveguide; millimeter-wave; quasi-TEM.*

1. Introduction:

Planar transmission lines are essential elements in the development of microwave, millimeter-wave, and high-frequency electronic circuits. They provide a practical means of transferring electromagnetic energy between different components while allowing the transmission structure and circuit elements to be integrated on a planar substrate. With the continuing development of compact and high-frequency systems, different planar transmission-line configurations have been developed to meet requirements associated with operating frequency, losses, impedance, fabrication, and circuit integration.

The electromagnetic behavior of a transmission line is determined by its physical geometry, dielectric environment, conductive boundaries, and operating frequency. Depending on the structure, electromagnetic energy may propagate in transverse electromagnetic (TEM), quasi-TEM, transverse electric (TE), or transverse magnetic (TM) modes. In a TEM mode, both electric and magnetic fields are completely transverse to the

direction of propagation, whereas in a quasi-TEM mode the fields are predominantly transverse with small longitudinal components.

Several planar configurations have been developed for different frequency ranges and applications. Important examples include image lines, microstrip, fin lines, inverted microstrip, slot lines, trapped inverted microstrip, coplanar waveguides, coplanar strip/differential lines, and stripline. Each structure has its own electromagnetic characteristics, advantages, and limitations.

The selection of a suitable planar transmission-line structure depends on operating frequency, transmission performance, losses, fabrication accuracy, component integration, and susceptibility to higher-order modes. At very high frequencies, radiation losses, fabrication tolerances, coupling, and unwanted modes become increasingly important. This paper therefore presents a theoretical study of different planar transmission-line structures and discusses their operating principles, propagation characteristics, frequency capabilities, losses, fabrication considerations, and practical limitations.

2. Theoretical Background:

Many planar transmission-line structures have been conceived, and new variants continue to be developed. Each configuration consists of conducting and dielectric regions arranged to control the propagation of electromagnetic energy. In most structures, the dielectric primarily supports the conducting pattern and influences wave propagation, whereas in an image line the dielectric slab itself forms the principal guiding region.

The choice of a transmission-line structure depends strongly on the type of circuit or subsystem and its operating frequency. For example, image lines are intended mainly for millimetric-wavelength applications, whereas microstrip can be used from low frequencies to the tens-of-gigahertz range. The electromagnetic mode is another important consideration. When the electric and magnetic fields are entirely transverse to the direction of propagation, the mode is TEM. When the fields are nearly transverse, the mode is described as quasi-TEM. In non-TEM structures, longitudinal field components become significant.




Figure 1: Common transmission-line structures suited to planar fabrication.

**3. Types of Planar Transmission Lines:****3.1 Image Line:**

At very high microwave frequencies, extending into the hundreds of gigahertz, the wavelength can become comparable with practical dielectric-slab dimensions. A continuous dielectric slab placed on a conducting backing form an image line. The structure behaves similarly to a dielectric waveguide and supports transverse electric (TE) and transverse magnetic (TM) modes, with fields influenced strongly by the dielectric-air interface. Typical dielectric materials include boron nitride, alumina, and high-resistivity silicon, and the slab is generally machined into an approximately rectangular form.

Image lines can exhibit high unloaded Q factors and are particularly relevant above 100 GHz. However, practical limitations include compatibility with active devices, mutual coupling, radiation from discontinuities and bends, and losses associated with dielectric-metal adhesives. These factors can reduce the loaded Q factor and complicate practical implementation.

3.2 Dielectric-Filled and Semicircular Waveguide Structures:

For operation around and above 100 GHz, dielectric-filled waveguides with approximately semicircular cross-sections have also been considered. Reported operation at lower frequencies has demonstrated high unloaded Q factors. Their potential benefits include low radiation loss at bends, high packing density due to inherent shielding, and reduced sensitivity to certain manufacturing irregularities. Further investigation of manufacturing parameters is nevertheless required for predictable engineering performance.

3.3 Microstrip:

Microstrip has a comparatively simple physical geometry, although its electromagnetic fields are complex. Detailed analysis can require elaborate mathematical treatment; however, quasi-TEM approaches combined with frequency-dependent expressions can provide satisfactory design accuracy for many applications. Micromachining permits microstrip to be fabricated on membranes with very little dielectric material, which can substantially reduce loss, particularly at millimeter-wave frequencies.

Microstrip structures may also be partially or completely shielded to reduce surface-wave effects. Such configurations are referred to as micro-shield lines. Microstrip is suitable for applications extending from a few gigahertz, or even lower frequencies, to at least several tens of gigahertz. At increasingly high frequencies, however, radiation and other losses rise, higher-order modes become more important, and fabrication tolerances become more difficult to maintain.

3.4 Fin Line:

Fin line consists of a dielectric substrate mounted within a fully shielding rectangular conducting enclosure. A metallic circuit is deposited on one side of the substrate, with a slot pattern forming the fin-line circuit. A continuous microwave short circuit to the upper and lower conducting walls is important for proper operation. Because the structure is associated with the E-plane of the electromagnetic field, fin-line circuits are commonly treated as E-plane integrated circuits and their dominant propagation is not TEM.



Important advantages of fin line include relatively low loss and comparatively simple fabrication. Applications have been investigated at frequencies extending to about 220 GHz. Fin line has also been used in bandpass filters, quadrature hybrids, waveguide transitions, balanced mixers, and impedance-transforming and filter networks.

3.5 Inverted Microstrip:

In inverted microstrip, the strip conductor is fabricated similarly to conventional microstrip, but the conductor on the opposite side of the substrate is absent. Instead, a ground plane is separated from the strip by an air space. Consequently, a large portion of the electromagnetic field exists in the air region. This arrangement permits operation at higher frequencies and provides a wider conductor for a specified characteristic impedance than conventional microstrip. The wider conductor can reduce conductor dissipation and relax fabrication tolerances, making the structure useful for lower-loss filters and impedance-transforming networks.

3.6 Slot Line:

A slot line consists of a dielectric substrate metallized on one side, with a narrow slot etched into the metallization. The structure has been used in a variety of microwave circuits, but it has several limitations. Characteristic impedances below approximately 60 ohms are difficult to obtain, registration can be challenging in structures involving metallization on opposite sides, and its Q factor can be lower than that of several other planar configurations. A related structure is the coplanar strip line (CPS), formed by restricting the conductors to two adjacent finite strips driven differentially.

3.7 Trapped Inverted Microstrip:

Trapped inverted microstrip (TIM) is derived from inverted microstrip by forming the ground plane as a slot- or channel-shaped section around the strip conductor. This arrangement provides additional grounding and shielding and can suppress some higher-order modes that might otherwise propagate. Inverted microstrip and TIM are potential candidates for millimetric-wave applications extending to and beyond approximately 95 GHz. Their implementation can, however, require tight control of conductor-to-ground spacing and channel dimensions, particularly in hybrid microwave integrated circuits.

3.8 Coplanar Waveguide:

A coplanar waveguide (CPW) has the signal conductor and ground conductors on the same side of the dielectric substrate and supports quasi-TEM propagation. Compared with microstrip, a smaller proportion of the electromagnetic field enters the substrate. In conventional CPW, the ground planes extend substantially, while finite-ground CPW can reduce coupling between adjacent and crossing lines. CPW has been applied in circuits ranging from individual components to complete amplifiers and subsystems. Semiconductor devices and MMIC chips can be connected across the intermetallic gaps, reducing the need for drilled vias. A conductor-backed CPW introduces metallization on the backside of the substrate and can be used to reduce losses.

3.9 Coplanar Strip and Differential Line:

Coplanar strip (CPS) and differential lines consist essentially of two conductors deposited on the same substrate without an additional conducting layer. The substrate primarily provides mechanical support, while the



dominant field distribution is generally quasi-TEM. When one conductor is grounded, the arrangement is known as CPS; when neither conductor is grounded and the structure is differentially driven, it is called a differential line. Differential interconnects are widely used in RF integrated circuits and high-speed digital systems. Their electrical characteristics can be affected by nearby metallic structures, particularly ground planes. Radiation and higher-order-mode issues can limit their use in some hybrid microwave implementations.

3.10 Stripline:

Stripline is a symmetrical planar transmission structure in which a central rectangular conductor is completely surrounded by dielectric material and enclosed between conducting ground surfaces. It can be regarded as a flattened form of a coaxial transmission line. Because the structure is fully filled with dielectric, propagation is fundamentally TEM and depends explicitly on the relative permittivity of the dielectric. Suspended stripline is obtained when the ground enclosure contains air gaps above and below the strip. Although such structures can exhibit relatively low loss and high Q, waveguide modes may be excited at higher frequencies. Reducing the separation between the walls or incorporating mode suppressors can help control these modes, although such measures may restrict component mounting and increase design complexity.

4. Discussion and Conclusion:

The theoretical study demonstrates that no single planar transmission-line configuration is suitable for all high-frequency applications. Each structure provides a particular combination of propagation characteristics, loss performance, frequency capability, fabrication requirements, and integration possibilities. Microstrip offers simple construction and broad applicability, whereas fin line, inverted microstrip, and TIM provide useful alternatives for higher-frequency operation. CPW and differential structures are attractive for integrated circuits because their conductors are accessible on the same surface, while stripline provides a symmetrical environment and TEM propagation. Image-line and related dielectric-guiding structures are relevant to very high-frequency and millimetric-wave applications but introduce additional fabrication and integration challenges.

At high frequencies, losses, radiation, higher-order modes, coupling, and manufacturing tolerances become increasingly significant. Consequently, practical systems may require more than one transmission-line technology, with suitable transitions used to transfer energy efficiently between structures. The comparative understanding developed in this study can assist in selecting planar transmission-line configurations according to the requirements of microwave and millimetre-wave circuits and subsystems.

References:

- [1] K. C. Gupta, R. Garg, I. J. Bahl, and P. Bhartia, Microstrip Lines and Slot lines, 2nd ed. Norwood, MA, USA: Artech House, 1996. This book specifically covers planar microwave transmission structures, including microstrip, slot line, coplanar waveguides, and fin lines.
- [2] R. Garg, I. J. Bahl, and M. Bozzi, Microstrip Lines and Slot lines, 3rd ed. Boston, MA, USA: Artech House, 2013.



- [3] D. M. Pozar, Microwave Engineering, 4th ed. Hoboken, NJ, USA: Wiley, 2012. The book includes dedicated material on transmission-line theory, transmission lines and waveguides, and microwave circuits.
- [4] K. C. Gupta, R. Garg, and I. J. Bahl, Microstrip Lines and Slot lines. Norwood, MA, USA: Artech House, 1979.
- [5] C. Nguyen, "Mode-Matching Method," in Analysis Methods for RF, Microwave, and Millimeter-Wave Planar Transmission Line Structures. Wiley, 2001, ch. 8.